

How to reset WGDashboard access credentials

The administrator username and password is stored on your server in the following configuration file: /wgdashboard/src/wg-dashboard.ini

You can reset the credentials to the default admin/admin by following these steps:

1. Connect to your server [via SSH](#)
2. Execute the following command (you can paste it into your SSH client):

```
sed -i '2 c\username = admin' /wgdashboard/src/wg-dashboard.ini && sed -i '3 c\password =  
8c6976e5b5410415bde908bd4dee15dfb167a9c873fc4bb8a81f6f2ab448a918' /wgdashboard/src/wg-dashboard.ini &&  
systemctl restart wg-dash
```

3. Wait for WGDashboard to reset (it should take under a minute).
4. Head over to your WGDashboard page, and use "admin" for both the uername and password.
5. Once logged in, change your username and password, as per the [Wireguard template](#) instructions.